

4" LED GIMBAL DOWN LIGHT INSTALLATION INSTRUCTION

PLEASE FIND A QUALIFIED ELECTRICIAN FOR INSTALLATION. Please read carefully and save these instructions, you may need them at a later date.

GENERAL: ALL ELECTRICAL CONNECTIONS MUST BE IN ACCORDANCE WITH LOCAL AND NATIONAL ELECTRICAL CODE (N.E.C.) STANDARDS. IF YOU ARE UNFAMILIAR WITH PROPER ELECTRICAL WIRING CONNECTIONS OBTAIN THE SERVICES OF A QUALIFIED ELECTRICIAN.

- Remove the trim from the box and make sure that no parts are missing by referencing the parts illustrations.
- This retrofit assembly is accepted as a component of a LED luminaire where the suitability of the combination shall be determined by authorities having jurisdiction.

WARNING - RISK OF FIRE OR ELECTRIC SHOCK

- Disconnect main power at the fuse or circuit breaker before installing or servicing the fixture.
- Do not make or alter any open holes in an enclosure of wiring or electrical components during kit installation.
- To prevent wiring damage or abrasion do not expose wiring to edges of sheet metal or other sharp objects.
- Suitable for wet locations.
- Suitable for Type IC or suitable for Type Non-IC.
- Use only in open luminaires.
- This device is not intended for use with emergency exits.

Model	Input Voltage	Frequency	Power	CCT	Rated Current(max)	Dimmable
AN-DLG10W-5CCT	AC 120V	50/60Hz	10W	27K/30K/35K/40K/50K	0.1A	120V Triac Dimmable

1 WARNING - RISK OF ELECTRIC SHOCK DISCONNECT MAIN POWER AT FUSE OR CIRCUIT BREAKER BEFORE INSTALLING OR SERVICING THIS FIXTURE.

INCANDESCENT HOUSING INSTALLATION

1. Disengage the socket from the socket bracket, if necessary. (Fig. 1)
2. Thread the socket adapter into the socket. (Fig. 2)
3. Connect the orange connectors together. (Fig. 3)
4. Tuck all wires in the can and carefully push the retrofit trim into the can. **Note:** To provide enough room in shallow cans, carefully position the socket adapter and socket alongside of the LED Driver prior to inserting the retrofit into the can. (Fig. 4)
5. Once the fixture is mounted in the ceiling, caulk the space between the ceiling and the shell, if necessary. (Fig. 5)








LED HOUSING INSTALLATION

1. Plug the female connector of the retrofit trim into the male connector of the housing. (Fig. 3)
2. Tuck all the wires into the can and carefully push the retrofit trim into the can. **Note:** To provide enough room in shallow cans, carefully position socket adapter and socket alongside of the LED driver prior to inserting the retrofit trim into the can. (Fig. 4)
3. Once the fixture is mounted in the ceiling, caulk the space between the ceiling and the shell, if necessary. (Fig. 5)

DIMMING - 120V

Dimming performance may depend on the dimmer, the range adjustment setting (for dimmers with brightness range adjustments), the wiring method, and/or the number of LED modules installed onto the dimmer circuit.

- For the latest list of compatible dimmers please visit our website.
- For best results, it is recommended to install a minimum of four LED modules onto one dimmer.
- Before turning on the LED lights, set dimmer position at maximum before adjusting to a lower light level.
- Please follow the dimming control manufacturer's instructions for installation of all dimming controls.



Specifications subject to change without notice. Photos and line drawings may not be to scale and are for general reference only.